

The background features a vibrant, multi-colored abstract design. On the left, there are horizontal, wavy bands of color in shades of red, orange, yellow, and green. On the right, a bright white light source emits a series of sharp, triangular rays in various shades of blue and cyan, creating a sunburst effect that spreads across the right half of the image.

cisco *Live!*

Let's go

#CiscoLiveAPJC



The bridge to possible

Manage, Operate, and Optimise High-Performance Storage Area Networks

Getting your SAN to perform at its best

Roman Vitasek
Technical Solutions Architect
BRKDCN-3641

CISCO *Live!*

#CiscoLiveAPJC

Cisco Webex App


Questions?

Use Cisco Webex App to chat with the speaker after the session

How


- 1 Find this session in the Cisco Live Mobile App
- 2 Click “Join the Discussion”
- 3 Install the Webex App or go directly to the Webex space
- 4 Enter messages/questions in the Webex space

Webex spaces will be moderated by the speaker until December 22, 2023.



<https://ciscolive.ciscoevents.com/ciscolivebot/#BRKDCN-3641>

Exponential Data Growth



1 Yottabyte

by 2030


<https://insightsndata.com/the-exponential-growth-of-data-understanding-the-implications-and-preparing-for-the-future-ee07c380e98d>

Agenda


- Overview
- Common Architectures
- Understanding and Detecting SAN Congestion
- Preventing and Predicting SAN Congestion
- Summary

Cisco MDS 9000 Switch Hardware

SAN Directors




Modules



● 8/16/32/64G FC ● 4/8/16/32G FC ● 2/4/8/10/16G FC


Fabric Switches



● SAN Analytics ● FCIP ● FICON

Line-rate, non-blocking, non-oversubscribed, since 2013

Unique Investment Protection



Non-disruptive multi-generation upgrades

Multi-generation optics support

8/16/32/64G FC optics

Multi-generation module support

16/32/64G FC module

Multi-generation FC speed support


2/4/8/10/16/32/64G FC

Cisco MDS SAN directors: Single chassis multi-generation support

Agenda

- Overview
- [Common Architectures](#)
- Understanding and Detecting SAN Congestion
- Preventing and Predicting SAN Congestion
- Summary

Pod Architecture




Benefits

- Best at containing SAN congestion / slow drain within the rack
- No effect on other racks while one rack is under maintenance

Challenges

- Requires a different data center operational model

Edge-Core Design




Benefits

- Most deployed option
- Tried and tested

Challenges

- Prone to congestion and slow drain

Consolidated Fabric




Benefits

- Fewer switches
- Less operational overhead
- Reduced congestion / slow drain

Challenges

- Watch out for cable length
- Scaling beyond 768 devices

Large Scale Edge-Core-Edge Design



Benefits


- Best at scaling up an existing fabric
- Long term investment protection (20 years)

Challenges


- Prone to congestion and slow drain
- Requires strict processes around operation control

Typical LAN and SAN Designs


LAN and SAN Separation



Convergence at ToR switch



Converged at ToR switches and host




Agenda

- Overview
- Common Architectures
- Understanding and Detecting SAN Congestion
- Preventing and Predicting SAN Congestion
- Summary




Troubleshooting SAN congestion is like
searching for a needle in a haystack

Fibre Channel Flow Control




Common Causes of SAN Congestion



Common Causes of SAN Congestion

Slow Drain


Tx B2B credit starvation



Common Causes of SAN Congestion

Slow Drain

Tx B2B credit starvation




Frames are not dropped in FC fabric. Rather, they consume switch buffers causing a fabric-wide congestion.

Common Causes of SAN Congestion


Slow Drain

Tx B2B credit starvation



Overutilisation

Receive data rate on ISL port is faster than the host port speed



Frames are not dropped in FC fabric. Rather, they consume switch buffers causing a fabric-wide congestion.

Congestion Detection

- Most problems start when a port hits 0 Tx/Rx B2B credits
- Increment Tx/Rx “**B2B Transitions to Zero**” counter
- Additional counters to provide further context:



TxWait
2.5µs



Slowport-monitor
1-500ms



Tx-datarate
%




Timeout-drops
500ms



Credit-Loss-Recovery
1s / 1.5s

NDFC Congestion Analysis

- NDFC provides online congestion analysis, and displays list of devices with potential slow drain issues:



Agenda


- Overview
- Common Architectures
- Understanding and Detecting SAN Congestion
- Preventing and Predicting SAN Congestion
- Summary

SAN Congestion Management

Reactive

Proactive

Predictive



Detecting SAN
Congestion


(TxWait, RxWait, Tx-datarate)



Preventing SAN
Congestion

(Dynamic Ingress Rate Limiting)

SAN Congestion Management Innovations



Prevent SAN Congestion with MDS DIRL – Cisco Exclusive capability/patent

Common Causes of SAN Congestion

Slow Drain

Overutilisation

Different Detection


On the switch port connected to the culprit device

Similar Effects

On fabric and victim devices

Same Root Cause

The culprit device is receiving more than it can ingest




The Root Cause of SAN Congestion

The Root Cause

I-1 is receiving more than it can ingest

Why is I-1 receiving more than it can ingest?

...because I-1 is asking for it.



The Solution


Cisco Dynamic Ingress Rate Limiting



I-1 is asking for more than it can ingest

DIRL limits I-1's asking rate to reduce its receiving rate

DIRL dynamically changes I-1's asking rate to adapt to its traffic profile



The Solution


Cisco Dynamic Ingress Rate Limiting



I-1 is asking for more than it can ingest

DIRL limits I-1's asking rate to reduce its receiving rate

DIRL dynamically changes I-1's asking rate to adapt to its traffic profile



DIRL prevents SAN Congestion due to Slow-Drain and Overutilisation.

Cisco Dynamic Ingress Rate Limiting



End-device Independent

No need to upgrade end-devices.



Adaptive

Dynamically adjusts to the traffic profile of the host.



No Side Effects

Rate limits congested hosts only.



Easy Adoption

Software-only upgrade.



Affordable


No additional license needed.



Topology Independent

Edge-core, edge-core-edge, or collapsed core topologies.

Without Cisco DIRL



With Cisco DIRL




SAN Congestion Management

Reactive

Proactive

Predictive



Detecting SAN
Congestion

(TxWait, RxWait, Tx-datarate)



Preventing SAN
Congestion

(Dynamic Ingress Rate Limiting)




Predicting SAN
Congestion


(SAN Analytics and Insights)



Where is the Problem?



NVMe and SCSI I/O Visibility Using SAN Analytics



Cisco SAN Analytics Flow Metrics

Write I/O Operation

New to Cisco MDS 64G Switches

Host Response Latency (HRL)

Exchange Completion Time (ECT)

Data Access Latency (DAL)

Initiator

MDS

Target

Initiate Write Command

Transfer Ready


Data Frames

Data Frames


Response

Pinpointing Storage I/O Performance Issues

Storage performance is degraded due to delay caused by **storage array**



Storage performance is degraded due to delay caused by **host**



Write Transaction


Initiator



MDS




Target



Where is the bottleneck ?


Deployment Models

Storage Ports




Closest to Storage

ISL Ports



High capacity 64G ISLs


Host Ports



Closest to Apps

- Inspection of traffic at least once in the end-to-end data path is enough
- Avoid double inspection of traffic
- Design for uniform utilisation of the NPU
- Most customers are enabling analytics on storage ports

Cisco SAN Analytics Scale for Always-on Visibility



MDS 9700

SAN Analytics

- 100K flows monitored per MDS 9700
- Real-time (microsecond) visibility into any flow using on-switch CLI
- 30-second export interval to NDFC


```
switch# ShowAnalytics --info --initiator-itl
VSAN|I|T|L | Avg IOPS | Avg Thput. (B/s) | Avg ECT (used) |
|-----|-----|-----|-----|
| Read|Write | Read|Write | Read|Write |
4|0x650060|0x650040|0000-0000-0000-0000 | 2355|2311 | 9646080|9467904 | 282|248 |
4|0x650060|0x650040|0001-0000-0000-0000 | 2313|2330 | 9477120|9543680 | 282|236 |
4|0x650060|0x650040|0002-0000-0000-0000 | 2324|2337 | 9519104|9574400 | 295|236 |
4|0x650061|0x650041|0001-0000-0000-0000 | 2235|2294 | 9567232|9397248 | 274|264 |
4|0x650061|0x650041|0000-0000-0000-0000 | 2283|2333 | 9351168|9559040 | 284|246 |
4|0x650061|0x650041|0002-0000-0000-0000 | 2302|2354 | 9431040|9645056 | 289|282 |

switch# ShowAnalytics --info --target-itl --target 0x2203e2
Interface f012/16
VSAN|I|T|L | Avg IOPS | Avg Thput. (B/s) | Avg ECT (used) |
|-----|-----|-----|-----|
| Read|Write | Read|Write | Read|Write |
1|0x220381|0x2203e2|0000-0000-0000-0000 | 2323|2301 | 9518080|9427968 | 145|105 |
1|0x220381|0x2203e2|0002-0000-0000-0000 | 2293|2343 | 9395200|9597952 | 148|102 |
1|0x220381|0x2203e2|0001-0000-0000-0000 | 2282|2341 | 9349120|9591808 | 145|106 |
```


NDFC SAN Insights

- 1 million flows received from multiple switches
- Anomaly detection
- Automatic baseline, deviations, trending
- End-to-end correlation


NDFC SAN Insights



NDFC SAN Insights



Cisco UCS and VM Traffic Visibility using NDFC



End-to-end Visualization

VM hosted on UCS servers, service profiles, vHBA/vNIC names, FI ports, etc.

Traffic Trends and Seasonality


For every vNIC/vHBA and service profile

Inventory

Server memory, CPU, serial numbers, etc.

End-to-end visibility into I/O flows is also available in non-UCS environments

NDFC SAN One View



Agenda


- Overview
- Common Architectures
- Understanding and Detecting SAN Congestion
- Preventing and Predicting SAN Congestion
- Summary

Summary

Reactive

Proactive

Predictive



Detecting SAN
Congestion

(TxWait, RxWait, Tx-datarate)



Preventing SAN
Congestion

(Dynamic Ingress Rate Limiting)



Predicting SAN
Congestion

(SAN Analytics and Insights)



Did you know?

You can have a
one-on-one session with
a technical expert!

Visit Meet the Expert in The HUB
to meet, greet, whiteboard & gain
insights about your unique questions
with the best of the best.



Meet the Expert Opening Hours:

Tuesday	3:00pm – 7:00pm
Wednesday	11:15am – 7:00pm
Thursday	9:30am – 4:00pm
Friday	10:30am – 1:30pm

Session Surveys

We would love to know your feedback on this session!

- Complete a minimum of four session surveys and the overall event surveys to claim a Cisco Live T-Shirt



Continue your education



- Visit the Cisco Showcase for related demos
- Book your one-on-one Meet the Expert meeting
- Attend the interactive education with DevNet, Capture the Flag, and Walk-in Labs
- Visit the On-Demand Library for more sessions at www.CiscoLive.com/on-demand



The bridge to possible

Thank you

CISCO *Live!*

#CiscoLiveAPJC

The background is a vibrant, abstract graphic. On the left, there are horizontal, wavy bands of color in shades of red, orange, yellow, and green. On the right, a bright white light source emits a series of colorful rays in shades of blue, green, and yellow, creating a sunburst effect.

cisco *Live!*

Let's go

#CiscoLiveAPJC